

WHEN TO COMPLETE – Before the start of any DE-ISOLATION & RE-ENERGIZING activities			
Confirm each control / safeguard below before starting works	Guidance for confirming each control/safeguard	Person(s) Performing Work	Start Work Verifier
I HAVE CONFIRMED:			
(1) Circuit, system, and/or equipment to be de-isolated/re-energized is the one identified in the isolation plan or drawing	<ul style="list-style-type: none">Tags or markings identify the circuit, system, and/or equipment to be de-isolated/re-energized <p>Note: Confirm circuit, system, and/or equipment is ready to be de-isolated and re-energized (e.g. all work has been completed)</p>		
(2) Isolation devices are removed per the isolation plan or drawing	<ul style="list-style-type: none">Physically inspect:<ul style="list-style-type: none">Work area to confirm all mechanical, process and electrical isolations were removed per planBleed and vent points to confirm they are closed/open per plan or procedure		
(3) Any personnel affected by the re-energizing activity have been notified	<ul style="list-style-type: none">Personnel in/near the work area or affected by the re-energizing of circuit, system and/or equipment are aware it is ready to be put back in servicePersonne are not in the Line of Fire of re-energized potential hazardous energy sources (e.g. electrical, pressure, hydraulic, mechanical etc.)		
(4) The circuit, system, and/or equipment is ready to be re-energized per plan or drawing	<ul style="list-style-type: none">Circuit, system and/or equipment is ready to be re-energized per the isolation plan or system/equipment operating procedure.		
Confirm these controls/safeguards are in place and verified prior to starting work. Stop and seek help if anything changes.			
	Printed Name & Role	Signature	Date
Start Work Verifier			

